

## Technical Parameters:

- Product Size:110\*90\*25mm
- Package Size:145\*95\*50mm
- Supply Voltage:DC5V-24V
- Connecting mode:common anode
- Weight:270g
- Output current:≤10A(each channel)
- Output power:360W



Push button A and button D simultaneously for one second before you start the remote controller the first time.

## Direction for use:

- 1.Connect the load wire at first,then the power wire:Never connection two wires directly in case of short circuit.
- 2.According to mode key to choose the different changing mode every time,when the key is pressed,the effects is changed,functional changes have been listed as follows:
- 3.Press speed key can change every effect's speed changing progression,"S/B" add one when you press the button every time,but "S/B-" will subtract one,totally 10 progressions to change the speed.
- 4.Standard functional changes have been listed as follows:

Mode			Mode		
1	Static	Brightness adjustable	9	Seven color jumpy changing	Speed is adjustable
2	Static green	Brightness adjustable	10	Three color gradual changing	Speed is adjustable
3	Static Blue	Brightness adjustable	11	Seven color jumpy changing	Speed is adjustable
4	Static red and green	Brightness adjustable	12	RGB quickly change	Speed is adjustable
5	Static red and blue	Brightness adjustable	13	Mode 9 and mode 11	Speed is adjustable
6	Static green and blue	Brightness adjustable	14	RGB gradual changing at the same	Speed is adjustable
7	Static red and green and blue	Brightness adjustable	15	RGB changing like running water	Speed is adjustable
8	Three color jumpy changing	Speed is adjustable			

# Conjunction diagram

